

PHYTEC

Develop.phytec

Pages

Blog

SPACE SHORTCUTS

PHYTEC Products

Troubleshooting articles

How-to articles

Application Notes

Technical Support Contacts

PAGE TREE

phyCORE-AM57x

phyCORE-i.MX7

phyCORE-i.MX6UL

phyCORE-i.MX6

phyCORE-AM335x

phyCORE-OMAP44xx

phyFLEX-i.MX 6

phyCORE-Vybrid

phyBOARD-i.MX6UL Segin

phyBOARD-i.MX6 Mira

phyBOARD-i.MX7 Zeta

phyBOARD-AM335x Wega

Cosmic Board (Vybrid)

phyCORE-AM57x Rapid Developr

phyCORE-iMX7 Development Kit

phyCORE-i.MX6UL Development

phyCORE-AM335x Rapid Develop

phyFLEX-i.MX6 Rapid Developme

phyCORE-Vybrid Rapid Developrr

phyCORE-OMAP44xx Developme

PHYTEC Legacy Products

Hardware Accessories

Quick Start Guides

Software BSPs

BSP-Android-TI-AM57x-PD17.1

BSP-Android-TI-AM57x-PD17.1

BSP-Freertos-NXP-iMX7-ALPHA1

BSP-RTOS-TI-AM57x-PD17.1.0

BSP-RTOS-TI-AM57x-PD17.1.1

BSP-RTOS-TI-AM57x-PD18.1.0

BSP-Yocto-FSL-iMX7-ALPHA1-R

BSP-Yocto-FSL-iMX7-ALPHA2-R

BSP-Yocto-FSL-iMX7-PD17.1.0-R

BSP-Yocto-FSL-iMX7-PD17.1.1-R

BSP-Yocto-TISDK-AM57xx-PD18.2.0 Release Notes

Operating System	Linux
BSP Release Status	RELEASED
Release Date	05 Oct 2018
Repository	PHYTEC Public Repos
Binaries	BSP-Yocto-TISDK-AM57xx-PD18.2.0

- Introduction
- Versioning
 - Software
 - Yocto Machine Configuration Table
 - Linux Device Tree Summary
 - Compatible Hardware
 - Supported Hardware Versions
 - Compatible Expansion Boards and Accessories
- BSP Download
- Quickstart
- BSP Features
- New In This Release
- Fixed In This Release
- Known Issues
 - Texas Instruments Known Issues (Kernel)
 - Texas Instruments Known Issues (U-Boot)
- Technical Support

Introduction

This BSP provides a basis for development, deployment and execution of Linux based applications on the phyCORE-AM57x System on Module (SOM). For detailed information on the various software components included in the release and how to use them, please refer to the [Quickstart](#).

Versioning

Software

Linux Kernel	4.9.41 (Based on TI SDK 04.01)
U-boot	2017.01 (Based on TI SDK 04.01)
Yocto	2.2 (Morty) (Based on TI SDK 04.01)
Host OS	Tested on 64-bit Ubuntu 16.04 LTS
Qt	5.7.1
OpenCL	1.1.14
OpenCV	3.1
Wayland	1.11
Gstreamer	1.8.3

- BSP Yocto FSL iMX7 PD17.2.1 R
- BSP Yocto FSL iMX7 PD18.1.0 R
- BSP Yocto FSL iMX7 PD18.1.1 R
- BSP Yocto FSL iMX7 PD18.2.0 R
- BSP Yocto FSL iMX7 PD18.2.1 R
- BSP-Yocto-TISDK-AM57xx-PD1
- BSP-Yocto-TISDK-AM57xx-PD1
- BSP-Yocto-TISDK-AM57xx-PD1
- BSP-Yocto-TISDK-AM57xx-PD1
- **BSP-Yocto-TISDK-AM57xx-P**
- BSP Yocto Yogurt AM335x PD1
- BSP Yocto Yogurt i.MX6 PD16.1
- BSP Yocto Yogurt i.MX6 PD16.1
- BSP Yocto Yogurt i.MX6UL PD1
- BSP Yocto Yogurt i.MX6UL PD1
- Cosmic Board-Vybrid Linux BSF
- i.MX6 PD15.3.0
- i.MX6 PD15.3.1
- phyBOARD-Mira i.MX6 PD15.2.
- phyBOARD-Mira i.MX6 PD15.X
- phyBOARD-Segin-i.MX6UL-ALF
- PhyBOARD-WEGA-AM335x Lin
- PhyBOARD-WEGA-AM335x Lin
- PhyBOARD-WEGA-AM335x Lin
- PhyBOARD-WEGA-AM335x Lin
- PhyBOARD-WEGA-AM335x PD
- PhyBOARD-WEGA-AM335x PD
- PhyBOARD-Zeta i.MX7 PD16.1-
- phyCORE-AM57xx-PD15.1-rc1
- phyCORE-AM57xx-PD15.1-rc2
- phyCORE-AM57xx-PD15.1-rc3
- phyCORE-AM57xx-PD15.1-rc4
- phyCORE-AM57xx-PD15.1-rc[1
- PhyCORE-AM335x Android BSF
- PhyCORE-AM335x Android BSF
- PhyCORE-AM335x Compact 7 |
- PhyCORE-AM335x Compact 7
- PhyCORE-AM335x Compact 7
- PhyCORE-AM335x Linux BSP-F
- PhyCORE-AM335x Linux BSP-P
- PhyCORE-AM335x Linux BSP-P
- PhyCORE-AM335x Linux BSP-P
- PhyCORE-AM335x PD15.1.0 Re
- PhyCORE-AM335x PD15.1.1 Re
- PhyCORE-AM335x RDK PD15.2

Yocto Machine Configuration Table

This BSP releases supports the phyCORE-AM57xx Rapid Development Kit (RDK) and also allows configuration options for different SOMs to be used with the RDK carrier board (PCM-948). By default, only the standard kit configuration will be in the table. If you have a different SOM, use the filters below to search by the SOM part number. The U-Boot defconfig and kernel device tree file names are important when creating custom U-Boot and Linux kernel images outside of Yocto development, or modifying Yocto source for further use.

Kit Part Number =

KPCM-057-L ✕

SOM Part Number =

Click and start typing

Yocto Machine Config	Kit Part Number	SOM Part Number (Click Here for description)
am57xx-phycore-rdk	KPCM-057-L, KPCM-057-SYS	PCM-057-10200110I, PCM-057-10201111I, PCM-057-10203110C, PCM-057-10203111I, PCM-057-40200110C, PCM-057-40201111I, PCM-057-40A00111I, PCM-057-41201111I, PCM-057-41300111I, PCM-057-50201111I, PCM-057-50500111I,
am5728-phycore-rdk	KPCM-057-L, KPCM-057-SYS	PCM-057-10200110I, PCM-057-40200110C, PCM-057-40A00111I, PCM-057-41300111I, PCM-057-50500111I,

Linux Device Tree Summary

- PhyCORE-AM3517 Compact 7
 - PhyCORE-AM3517 Compact 7
 - PhyCORE-AM3517 Linux BSP-F
 - PhyCORE-AM3517 Linux BSP-I
 - PhyCORE-i.MX35 CE 6.0 BSP-Pl
 - PhyCORE-i.MX35 Linux BSP-PD
 - PhyCORE-i.MX35 Linux BSP-PD
 - PhyCORE-LPC3250 CE 6.0 BSP-
 - PhyCORE-LPC3250 Linux BSP R
 - PhyCORE-OMAP44xx Android I
 - PhyCORE-OMAP44xx Compact
 - PhyCORE-OMAP44xx Compact
 - PhyCORE-OMAP44xx Linux BSF
 - PhyCORE-OMAP44xx Linux BSF
 - PhyCORE-OMAP44xx Linux BSF
 - PhyCORE-OMAP4430 Linux BS
 - PhyCORE-Vybrid Linux BSP-PD
 - PhyCORE-Vybrid Linux BSP-PD
 - PhyCORE-Vybrid Linux BSP-PD
 - PhyCORE-Vybrid MQX BSP-PD
 - phyFLEX-i.MX6 3.14-PL15.1.0 R
 - phyFLEX-i.MX6 RDK PD15.1.1 B
 - phyFLEX-i.MX6 RDK PD15.1.1 R
 - PhyFLEX-i.MX6 Compact 7 BSP
 - PhyFLEX-i.MX6 Compact 7 BSP
 - PhyFLEX-i.MX6 Compact 7 BSP
 - PhyFLEX-i.MX6 Linux BSP-PD12
 - PhyFLEX-i.MX6 Linux BSP-PD13
 - PhyFLEX-i.MX6 Linux BSP-PD13
 - PhyFLEX-i.MX6 Linux BSP-PD1.
 - PhyFLEX-i.MX6 Linux BSP-PD13
 - PhyFLEX-i.MX6 Linux BSP-PD13
 - PhyFLEX-i.MX6 Linux BSP-PD13
 - PhyFLEX-i.MX6 Linux BSP-PD14
 - PhyFLEX-i.MX6 Linux BSP-PD14
 - phyFLEX-IMX6-PD15.1.0 BSP R
- BSP Reference Guides

➤ PHYTEC USA Newsletter
- phyCORE-AM65x
 - phyCORE-AM65x Rapid Developr
 - phyCORE-i.MX8 X

This is a summary of how the device tree files and the various includes are broken down, using the am57xx-phycore-rdk (minimal configuration) as an example.

Hardware Target	Device Tree File Descriptions	Filename
phyCORE-AM57xx RDK	Default dts Build Target	am57xx-phycore-rdk.dts
	SOM (<i>superset</i>) - <i>enables all SOM features</i>	am57xx-phycore-common.dtsi
	SOM (silicon-specific) - <i>adds support and enables silicon-specific features</i>	am571x-phycore-som.dtsi
	SOM Variant - <i>excludes features not supported by the BOM population options for PCM-057-10203110C</i>	am571x-pcm-057-10203110c.dtsi
	Carrier Board	am571x-pcm-948.dtsi
	WiLink8 WiFi Module	am57xx-phytec-wlan-wilink8.dtsi

Compatible Hardware

Supported Hardware Versions

Part Number =

Click and start typing

Configuration Details =

Click and start typing

Hardware Description	Part Number	Configuration Details (DDR3 / DDR ECC / eMMC or NAND / QSPI NOR / Controller / EEPROM / Ethernet PHY / RTC / Temp)	PCB Version
phyCORE-AM57xx SOM	PCM-057-10200110I.A0	1GB (1 bank) / No / 4GB eMMC / No / AM5728 / Yes / Yes / No / Industrial	1428.3
	PCM-057-10201111I.A0	1GB (1 bank) / No / 4GB eMMC / No / AM5726 / Yes / Yes / Yes / Industrial	1428.3
	PCM-057-10203111I.A0	1GB (1 bank) / No / 4GB eMMC / No / AM5716 / Yes / Yes / Yes / Industrial	1428.3
	PCM-057-40200110C.A0	2GB (2 banks) / No / 4GB eMMC / No / AM5728 / Yes / Yes / No / Commercial	1428.3
	PCM-057-40201111I.A0	2GB (2 banks) / No / 4GB eMMC / No / AM5726 / Yes / Yes / Yes / Industrial	1428.3
	PCM-057-40A00111I.A0	2GB (2 banks) / No / 1GB NAND / No / AM5728 / Yes / Yes / Yes/ Industrial	1428.3
	PCM-057-41201111I.A0	2GB (2 banks) / Yes / 4GB eMMC / No / AM5726 / Yes / Yes / Yes / Industrial	1428.3
	PCM-057-41201111I.A1	2GB (2 banks) / Yes / 4GB eMMC / No / AM5726 / Yes / Yes / Yes / Industrial	1428.3
	PCM-057-41300111I.A1	2GB (2 banks) / Yes / 8GB eMMC / No / AM5728 / Yes / Yes / Yes / Industrial	1428.3
	PCM-057-41300111I.A2	2GB (2 banks) / Yes / 8GB eMMC / No / AM5728 / Yes / Yes / Yes / Industrial	1428.3
	PCM-057-50201111I.A0	4GB (2 banks) / No / 4GB eMMC / No / AM5726 / Yes / Yes / Yes / Industrial	1428.3
	PCM-057-	4GB (2 banks) / No / 32GB eMMC / No /	1428.3

	505001111.A0	AM5728 / Yes / Yes / Yes / Industrial	
phyCORE-AM572x Carrier Board	PCM-948.A3		1435.2
	PCM-948.A4		1435.2

Module Name	Part Number	PCB Version	Description
7" Display with Capacitive Touch	LCD-018-070-KAP	1365.1	EDT ETM0700G0DH6 TTL 7" display with capacitive touch
Expansion Bus Prototyping Board	PCM-957	1351.0	Expansion Bus Breakout and Prototype Board
WiFi/Bluetooth Module	PCM-949	1418.0	TI WiLink8 Module
Camera Module	VM-009-M12	1339.0	ON Semi MT9M131 Module

BSP Download

Prebuilt images of BSP-Yocto-TISDK-AM57xx-PD18.2.0 can be downloaded from the link below:

[BSP-Yocto-TISDK-AM57xx-PD18.2.0 Release](#)

Quickstart

Quickstarts for BSP-Yocto-TISDK-AM57xx-PD18.2.0:

 [BSP-Yocto-TISDK-AM57xx-PD18.2.0 Quickstart](#)

BSP Features

Interface	Detail	Implemented	Tested	Status in Device tree	Notes
UART	uart3	Yes	Yes	Okay	Connector X18 (default serial cor
	uart4	Yes	No	Disabled ¹	
	uart5	Yes	Yes	Okay	Connector X17
	uart6	Yes	No	Disabled ¹	
	uart7	Yes	No	Disabled ¹	
	uart8	Yes	No	Disabled ¹	
	uart9	Yes	No	Disabled ¹	
	uart10	Yes	No	Disabled ¹	
I2C	i2c1	Yes	Yes	Okay	Available on expansion Conne X28
	i2c2	Yes	Yes	Okay	Connected to HDMI1_DDC

	i2c3	Yes	No	Disabled ¹	
	i2c4	Yes	Yes	Okay	Used for Audio Codec - available on expansion Connector X28
	i2c5	Yes	No	Disabled ¹	
Ethernet	cpsw_emac0 (RGMII0 on SoM)	Yes	Yes	Okay	RGMII0 - KSZ9031RNX SoM PHY Connector X7
	cpsw_emac1 (RGMII1 on CarrierBoard)	Yes	Yes	Okay	RGMII1 - KSZ9031RNX Connector X8
Display and Touch	Analog Touch Control 1	Yes	Yes	Okay	Capacitive: ETM-FT5x06 (on LCD-01) I2C4
	Analog Touch Control 2	No	No	Disabled	Resistive: STMPET150 (on CB), I2C4
	PWM Backlight	Yes	Yes	Okay ²	ehrpwm0 (EHRPWM1A on carrier board)
	24-bit LCD Interface	Yes	see Known Issues	Okay ²	LVDS Connector X23 requires LCD-01E
	HDMI	Yes	see Known Issues	Okay	hdmi1_ddc Connector X24 (encoder TPD12S48 carrier board)
McASP	mcasp1	Yes	Yes	Okay	
	mcasp2	Yes	No	Disabled ¹	
	mcasp5	Yes	No	Disabled ¹	
	mcasp6	Yes	No	Disabled ¹	
	mcasp7	Yes	No	Disabled ¹	
	mcasp8	Yes	No	Disabled ¹	
eMMC/SD/SDIO	mmc1	Yes	Yes	Okay	Connector X2
	mmc2	Yes	Yes	Okay	eMMC on SOM
	mmc3	Yes	Yes	Okay	Connector X26 (WiFi/BT connector)
USB	usb1	Yes	Yes	Okay	USB 3.0 Standard Connector X30 (HDMI only)
	usb2	Yes	Yes	Okay	USB 2.0 Mini-AB Connector X9 (default); signals may also be routed to (Standard-A)
CAN	can1	Yes	Yes	Okay	DB9 Connector X1
	can2	Yes	Yes	Okay	Pin Header Connector X5
MCSPi	spi1	Yes	Yes	Okay	Connector X28 (Expansion connector)

					enabled using spi on X_SPI1_nCS0
	spi2	Yes	No	Disabled ¹	
	spi3	Yes	No	Disabled ¹	
	spi4	Yes	No	Disabled ¹	
QSPI	qspi1	Yes	see Known Issues	Okay	NOR Serial Flash SOM
SATA	sata1	Yes	Yes	Okay	Connector X11 (S and X12 (power connector)
PCIe	pcie1	Yes	Yes	Okay	Connector X27 (PI6C557 4x PCIe connector)
IPU	ipu1	Yes	Yes	Okay	
	ipu2	Yes	Yes	Okay	
DSP	dsp1	Yes	Yes	Okay	
	dsp2	Yes	Yes	Okay ³	
GPIO	User Buttons and LEDs	Yes	Yes	Okay	
Memory	EEPROM	Yes	Yes	Okay	M24C32 on I2C1
	NAND (8/16 bit)	Yes	Yes	Okay ⁴	MT29F8G08ABAC connected to GPM
	QSPI NOR Flash	Yes	see Known Issues	Okay	N25Q128A connected to QSPI1_CS2
	eMMC	Yes	Yes	Okay	mmc2 on SOM
RTC	Internal AM57xx	Yes	Yes	Okay	Internal to processor
	PMIC TPS659037	Yes	Yes	Okay	TPS659037 I2C1
	External RTC	Yes	Yes	Okay	RV-4162-C7 on I2C2
Audio	Stereo Codec on CarrierBoard	Yes	Yes	Okay	TLV320AIC3007 codec; connected to McASP1 and I2C2
Communication	TiWi-BLE WiFi	No	No	Disabled	Connector X26
	TiWi-BLE Bluetooth	No	No	Disabled	Connector X26
	WiLink8 WiFi	Yes	Yes	Okay	Connector X26
Parallel Camera	VIN3 on i2c3	Yes	Yes	Okay ³	VM-009 at Connector X23 (phyCAM-P connector)
Hardware Acceleration	Graphics (PowerVR SGX544)	Yes	Yes	Okay ²	

[1] It may be possible to change the software configuration to utilize this interface even if it is not being set in the board's default configuration.

[2] Only enabled on AM5728 silicon variants

[3] Only enabled on AM572x silicon variants

[4] Only enabled with the PCM-057-40A00111I configuration, but would be possible with other PCM-057-xxAxxxxx variants.

New In This Release

- **General**
 - **The default prebuilt images and Yocto MACHINE target *am57xx-phycore-rdk* now represents a minimal configuration (PCM-057-10203110C).**
 - This enables the same default images to be flashed to every SOM with eMMC, without triggering a hardware issue related to unsupported silicon features.
 - The settings for DDR and the enabled interfaces follow this configuration accordingly, on the first boot (before the EEPROM is written), and if the EEPROM data is invalid.
 - **Support for phyCORE-AM57xx with AM5716 Silicon**
 - **Support for Additional SOM Variants:**
 - PCM-057-10203111I.A0
 - PCM-057-40A00111I.A0
- **Yocto**
 - **MACHINE:** Additional machine targets
 - am5716-phycore-rdk
 - am571x-pcm-057-10203110c
 - am571x-pcm-057-10203111i
 - am572x-pcm-057-40a00111i
- **Kernel**
 - **Devicetree:**
 - Split am57xx-phycore-som.dtsi (SOM) into common and silicon-specific dtsi files:
 - am57xx-phycore-common.dtsi
 - am571x-phycore-som.dtsi
 - am572x-phycore-som.dtsi
 - Split am57xx-pcm-948.dtsi (carrier board) into silicon-specific dtsi files:
 - am571x-pcm-948.dtsi
 - am572x-pcm-948.dtsi
 - Added support for additional SOMs and dtb targets for them in conjunction the phyCORE-AM57xx carrier board (PCM-948)
 - am571x-pcm-057-10203111i.dtsi → am571x-phycore-rdk-10203111i.dtb
 - am572x-pcm-057-10201111i.dtsi → am572x-phycore-rdk-10201111i.dtb
 - am572x-pcm-057-40a00111i.dtsi → am572x-phycore-rdk-40a00111i.dtb
- **U-Boot**
 - **General:**
 - **Support for phyCORE-AM57xx with NAND**
 - **Build:**
 - New defconfig targets
 - *am572x-phycore-rdk_nand_defconfig*: PCM-057-40A00111I SOM variant (2GiB DDR with NAND)
 - *am571x-phycore-rdk_256M16_x2_defconfig*: PCM-057-1xxx3xxxx SOM variants (1GiB DDR with AM5716 silicon)
 - **Devicetree:**
 - Split am57xx-phycore-som.dtsi (SOM) into common and silicon-specific dtsi files:
 - am57xx-phycore-common.dtsi
 - am571x-phycore-som.dtsi
 - am572x-phycore-som.dtsi
 - Split am57xx-pcm-948.dtsi (carrier board) into silicon-specific dtsi files:
 - am571x-pcm-948.dtsi
 - am572x-pcm-948.dtsi
 - Added support for additional SOMs and dtb targets for them in conjunction the phyCORE-AM57xx carrier board (PCM-948)
 - am571x-pcm-057-10203111i.dtsi → am571x-phycore-rdk-10203111i.dtb
 - am572x-pcm-057-10201111i.dtsi → am572x-phycore-rdk-10201111i.dtb
 - am572x-pcm-057-40a00111i.dtsi → am572x-phycore-rdk-40a00111i.dtb

Fixed In This Release

- **Kernel**
 - cpufreq driver is failing to load
- **U-Boot**
 - When building for any MACHINE target beside am572x-phycore-rdk, unless the SOM EEPROM is loaded with valid identification information, it will attempt and fail to load the am572x-phycore-rdk.dtb from /boot/.
 - PHYTEC EEPROM board strings are incorrectly returning the first result for a partial match

Known Issues

- **Yocto**

- **AM57X6:** All MACHINE targets for the AM5726- and AM5716-based SOMs are incompatible with building for the *arago-core-tisdk-image* image target.
 - Workaround: use the *phytec-tisdk-image* image target instead.
- **Chromium:** Although enabled in the TISDK, Chromium has been disabled for all phyCORE-AM572x builds due to the large amount of swap memory required for linking, and the time required to successfully build it.
 - Workaround to build Chromium (for am5728-based SOMs only):
 - Pay close attention to the information provided in the [Chromium developer's guide prerequisites section](#) and adjust your system accordingly.
 - Remove the line 'MULTIMEDIA_remove = "chromium-wayland"' from `${YOCTO_DIR}/sources/meta-phytec/conf/machine/include/am572x-phytec.inc` before building.

- **Kernel**

- **Display:** TI's Matrix-GUI demo only outputs to a single display. If both HDMI and a parallel display are connected, it will display on the parallel display, but the resolution may not be correct—behavior is inconsistent.
 - Workaround: only connect the one display that will be used, or do not use the matrix-gui demo.
- **QSPI:** Possible read failures on flash devices with HOLD function (Erratum i916). A software workaround has been implemented to limit QSPI to DIO-SPI mode. The hardware workaround is to disable internal pull-ups and add 10k pull-ups on X_QSPI1_D2 & X_QSPI1_D3
- **PCIe:** With cpufreq properly supported again, some PCIe x2 devices are hanging the system during boot.
 - Workaround: prevent frequency changes by disabling the CPUFREQ_DT in the kernel menuconfig, or remove the following code block from the *am57xx-phycore-common.dtsi* file:

```
&cpu0 {  
  
    vdd-supply = <&smps12_reg>;  
  
};
```

This is a temporary fix and should be resolved with the next release.

[Texas Instruments Known Issues \(Kernel\)](#)

[Texas Instruments Known Issues \(U-Boot\)](#)

Technical Support

For further support please visit [PHYTEC's Support Portal](#)